



TREND NETWORKS

SignalTEK CT

Upgrade Information



SignalTEK CT Software Release Notes

Version 1.0.44 – October 2023

- ☐ Updated LCD touchscreen driver to prevent false activations.
- ☐ Checks storage memory for bad areas to reduce likelihood of boot errors.

Version 1.0.36 – September 2020

Added Japanese language to user interface.

SignalTEK CT Software Update Procedure



**This update is not reversible to previous versions.
All saved data will be erased during the update. Ensure all saved data is backed up before
updating the software.**

1. Obtain a USB flash drive formatted to FAT or FAT32, NTFS formatted drives are not compatible. The maximum supported USB drive size is 16GB.
2. Copy the "SignalTEK-CT-md5.bin" upgrade file from your computer to the root of the flash drive.
3. Ensure that the tester is connected to the mains power supply or that the battery is fully charged.
4. Power on the tester and insert the flash drive.
5. Save the tester configuration to the flash drive. Select SETUP / SYSTEM / CONFIG / SAVE.
6. Save stored test results to the flash drive. Select JOBS / OPTIONS / ALL TO USB.
7. Update the system software. Select SETUP / SYSTEM / UPDATE.
8. Confirm the process by selecting UPDATE to begin.
9. Wait for the update to complete and the tester to restart. Select your language after restart.
10. Confirm the new software version by selecting SETUP / SYSTEM / ABOUT.
11. Load the previously saved tester configuration. Select SETUP / SYSTEM / CONFIG / LOAD.
12. Check the date and time settings. Select SETUP / SYSTEM / TIME.
13. The tester is now ready to use.

No update to remote handset is required for version 1.0.44.



TREND NETWORKS

TREND NETWORKS LIMITED
728 London Road
High Wycombe, Buckinghamshire HP11 1HE, UK
+44 (0)1925 428 380 | uksales@trend.networks.com
www.trend-networks.com

Specification subject to
change without notice.
E&OE.
© TREND NETWORKS
LIMITED 2023